

Stability Conditions of Zero Solution for Third Order Differential Equation in Critical Case

Thair Y . Thanoon

Saad F .AL-Azzawi

College of Computers and Mathematical Sciences
Mosul University

Received on:20/5/2007

Accepted on:28/6/2007

المخلص

هذا البحث سيدرس شروط استقرارية الحل الصفري في الحالة شبه الخطية لمعادلة تفاضلية من الرتبة الثالثة بالشكل :

$$y''' + p_1(t)y'' + p_2(t)y' + p_3(t)y = h(t, y, y', y'')$$

حيث ان

$$p_s = \pi^s [q_s + w_s(t)] \quad , \quad q_s \in C \quad , \quad w_s(t): \Delta \rightarrow C \quad , \quad s = 1,2,3$$
$$t \in \Delta = [a, \infty) \quad , \quad a \in N$$

ان المعادلة المميزة للمعادلة التفاضلية اعلاه لها زوج من الجذور المعقدة بالشكل :

$$\lambda_1 = -\lambda_2 = i\lambda_0 \quad , \quad \lambda_0 > 0$$

والجذر الاخر يحقق الخاصية $\text{Re } \lambda_3 < -M, M > 0$

ABSTRACT

In this paper, we study the conditions under which the zero solution is stable in the semi- linear case for certain third order differential equation of the form :

$$y''' + p_1(t)y'' + p_2(t)y' + p_3(t)y = h(t, y, y', y'')$$

Where

$$p_s = \pi^s [q_s + w_s(t)] \quad , \quad q_s \in C \quad , \quad w_s(t): \Delta \rightarrow C \quad , \quad s = 1,2,3$$
$$t \in \Delta = [a, \infty) \quad , \quad a \in N$$

The characteristic equation of the above differential equation has complex roots of the form :

$$\lambda_1 = -\lambda_2 = i\lambda_0 \quad , \quad \lambda_0 > 0 \quad \text{and the other root has the following}$$

property $\text{Re } \lambda_3 < -M, M > 0$.

1- INTRODUCTION

Critical cases in the theory of stability for differential equation means , that cases when the real part of all roots of the characteristic equation are nonpositive with the real part of at least one root being zero , other express which is neither stable nor unstable [3] .

In the critical case the non-linear terms begin to influence the stability of a stationary point and the investigation of the first approximation for stability is in general impossible .

In [4,5] studied the conditions of stability zero solution for certain differential equation in the semi-linear case when the characteristic equation has roots of the form : $\lambda_1 = i\lambda_0, \lambda_0 > 0$

and the others satisfying the property $Re \lambda_k < -M, M > 0, k = 2, \dots, n$.

[4,6] studied the same conditions to find the center of gravity for nonautonomous quasi-linear differential equation of n-th order .

In this paper, we study the conditions under which the zero solution is stable in the semi-linear case of differential equation which has the form :

$$y''' + p_1(t)y'' + p_2(t)y' + p_3(t)y = h(t, y, y', y'') \quad \dots(1)$$

Where

$$p_s = \pi^s [q_s + w_s(t)], q_s \in C, w_s(t): \Delta \rightarrow C, s = 1,2,3$$

$$t \in \Delta = [a, \infty), a \in N$$

$\pi^s(t)$ are continuous functions for all s and α times differentiable and satisfies the following conditions :

$$\pi : \Delta \rightarrow (0, \infty), \pi^{-2} \pi' = 0(1), t \rightarrow \infty$$

$$h : \Delta \times C^n \rightarrow C, |h(t, y, y', y'')| \leq L^* [|y| + |y'| + |y''|]^{1+\beta}$$

$L^* : \Delta \rightarrow [0, \infty), \beta \geq 0$ and the characteristic equation of (1) has roots, $\lambda_1 = -\lambda_2 = i\lambda_0, \lambda_0 > 0$ and the other root has the following property $Re \lambda_3 < -M, M > 0$.

2- Definitions :

Definition 1 [3] : The zero solution of the differential equation (1) is said to be stable as $t \rightarrow \infty$, if $\forall \varepsilon > 0$ there exist $\delta > 0$ such that the solution $y = y(t)$ of the differential equation (1) with the initial condition $|y(T)| < \delta$ satisfies the inequality $|y(t)| < \varepsilon, \forall t \geq T$

Definition 2 [3]: If the conditions of definition(1) are satisfied and $Lim_{t \rightarrow \infty} x(t) = 0(1)$ then , zero solution of (1) is said to be asymptotically stable .

3 – Helping Transformations

In order to find the conditions under which the zero solution of differential equation (1) is stable , we use the following lemmas :

Lemma 1 [2] :

The transformation ;

$$\left. \begin{aligned} y &= \pi \cdot Z_1 \\ y' &= \pi^2 \cdot Z_2 \\ y'' &= \pi^3 \cdot Z_3 \end{aligned} \right\} \dots(2)$$

transform the differential equation (1) to the differential system of the form :

$$\left. \begin{aligned} Z_1' &= -\pi^{-1}\pi'Z_1 + \pi Z_2 \\ Z_2' &= -2\pi^{-1}\pi'Z_2 + \pi Z_3 \end{aligned} \right\} \dots(3)$$

$$Z_3' = -p_3(t)\pi^{-2}Z_1 - p_2(t)\pi^{-1}Z_2 - (3\pi^{-1}\pi' + p_1(t)) Z_3 + F_1(t, z)$$

where

$$|F_1(t, z)| \leq L [Z_1 + \pi Z_2 + \pi^2 Z_3]^{1+\beta}, L=L^* \pi^{\beta-2}$$

Lemma 2 [2] :

The transformation ;

$$\mathbf{X} = \mathbf{BZ} \quad \dots(4)$$

where

$$B = \begin{bmatrix} (i\lambda_0)^2 + q_1(i\lambda_0) + q_2 & i\lambda_0 + q_1 & 1 \\ (-i\lambda_0)^2 + q_1(i\lambda_0) + q_2 & -i\lambda_0 + q_1 & 1 \\ 1 & 0 & 0 \end{bmatrix}$$

$$q_1, q_2 \in \mathbb{C}, \quad \det B = 2i\lambda_0$$

transform the differential system (3) to the system of the form :

$$\left. \begin{aligned} X_1' &= \pi[i\lambda_0 X_1 + (-(i\lambda_0)^3 - q_1(i\lambda_0)^2 - q_2 i\lambda_0 - q_3)X_3] + F_2 \\ X_2' &= \pi[q_1 X_1 + (-i\lambda_0 - q_1) X_2 + ((i\lambda_0)^3 + (i\lambda_0)^2 q_1 + i\lambda_0 q_2 - q_3)X_3] + F_2 \\ X_3' &= \pi\left[\frac{1}{2i\lambda_0} X_1 - \frac{1}{2i\lambda_0} X_2\right] \end{aligned} \right\} \dots(5)$$

where $\lim_{t \rightarrow \infty} \pi^{-2} \pi' = o(1)$, $\lim_{t \rightarrow \infty} W_s(t) = o(1)$,

$$|F_2| \leq M \left[\frac{[-\pi + \pi^2(-i\lambda_0 + q_1)]X_1 + [\pi - \pi^2(i\lambda_0 + q_1)]X_2 + [-2i\lambda_0 + \pi^2 2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0]X_3}{-2i\lambda_0} \right]^{1+\beta}$$

$M > 0$

Lemma 3 [2] :

By using the following transformation

$$\left. \begin{aligned} X_1 &= y_1 \\ X_2 &= y_2 \\ X_3 &= ky_1 + \bar{k}y_2 + y_3 \end{aligned} \right\} \dots(6)$$

where $k, \bar{k} \in \mathbb{C}$

we transform the differential system (5) into the following differential system :

$$\left. \begin{aligned} y_1' &= \pi[(i\lambda_0 + c_1 k) y_1 + (c_1 \bar{k}) y_2 + c_1 y_3] + F_3 \\ y_2' &= \pi[(q_1 + c_2 k) y_1 + (-i\lambda_0 - q_1 + c_2 \bar{k}) y_2 + c_2 y_3] + F_3 \\ y_3' &= \pi \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + c_2 k) \right] y_1 + \left[-\frac{1}{2i\lambda_0} - kc_1 \bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k}) \right] y_2 + \\ &\quad \left[-kc_1 - \bar{k}c_2 \right] y_3 - F_3[k + \bar{k}] \end{aligned} \right\} \dots(7)$$

$$|F3| \leq ML \left[\frac{(-\pi + \pi^2(-i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)])}{-2i\lambda_0} y_1 + \right. \\ \left. \frac{(\pi - \pi^2(-i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)])}{-2i\lambda_0} y_2 + \right. \\ \left. + \left[\frac{-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)}{-2i\lambda_0} \right] y_3 \right]^{1+\beta}$$

Now , we use the following lemma which leads to the auxiliary system :

Lemma 4 [5] :

the transform

$$\left. \begin{aligned} y_1 &= w_1 + bw_2 + b_3w_3 \\ y_2 &= bw_1 + w_2 + b_3w_3 \\ y_3 &= w_3 \end{aligned} \right\} \dots(8)$$

where $b, b_3 \in \mathbb{C}$, $b \neq \pm 1$

$$w_1' = \frac{\pi}{1-b^2} [i\lambda_0 + c_1k - b(q_1 + c_2k) + b_3(b-1) \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) \right. \\ \left. - \bar{k}(q_1 + c_2k) \right] + b[c_1\bar{k} - b(-i\lambda_0 - q_1 + c_2\bar{k}) + b_3(b-1) \\ \left. \left[-\frac{1}{2i\lambda_0} - kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right] \right]] W_1 + \\ \frac{\pi}{1-b^2} [b[i\lambda_0 + c_1k - b(q_1 + c_2k) + b_3(b-1) \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) \right. \\ \left. - \bar{k}(q_1 + c_2k) \right]] + c_1\bar{k} - b(-i\lambda_0 - q_1 + c_2\bar{k}) + b_3(b-1) \left[-\frac{1}{2i\lambda_0} - kc_1\bar{k} - \right. \\ \left. \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right]] W_2 + \\ + \frac{\pi}{1-b^2} [b_3[i\lambda_0 + c_1k - b(q_1 + c_2k) + b_3(b-1) \left[-k(i\lambda_0 + c_1k) - \bar{k}(q_1 + c_2k) \right] + c_1\bar{k} - \\ b(-i\lambda_0 - q_1 + c_2\bar{k}) + b_3(b-1) \left[-kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right]] + c_1 - bc_2 + b_3(b-1) \\ \left. \left[-kc_1 - \bar{k}c_2 \right] \right] W_3 + \frac{1}{1-b^2} F_4 [1 - b - b_3(b-1)(k + \bar{k})]$$

□

$$\begin{aligned}
 w_2' = & \frac{\pi}{1-b^2} \left[-b(i\lambda_0 + c_1k) + q_1 + c_2k + b_3(b-1) \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) \right. \right. \\
 & \left. \left. - \bar{k}(q_1 + c_2k) \right] + b[-bc_1\bar{k} - i\lambda_0 - q_1 + c_2\bar{k} + b_3(b-1) \right. \\
 & \left. \left[-\frac{1}{2i\lambda_0} - kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right] \right] W_1 + \\
 & \frac{\pi}{1-b^2} \left[b[-b(i\lambda_0 + c_1k) + q_1 + c_2k + b_3(b-1) \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) \right. \right. \right. \\
 & \left. \left. - \bar{k}(q_1 + c_2k) \right] \right] - bc_1\bar{k} - i\lambda_0 - q_1 + c_2\bar{k} + b_3(b-1) \left[-\frac{1}{2i\lambda_0} - kc_1\bar{k} - \right. \\
 & \left. \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right] W_2 \\
 & + \frac{\pi}{1-b^2} \left[b_3[-b(i\lambda_0 + c_1k) + q_1 + c_2k + b_3(b-1) \left[-k(i\lambda_0 + c_1k) \right. \right. \right. \\
 & \left. \left. - \bar{k}(q_1 + c_2k) \right] - bc_1\bar{k} - i\lambda_0 - q_1 + c_2\bar{k} + b_3(b-1) \left[-kc_1\bar{k} - \right. \right. \\
 & \left. \left. \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right] - bc_1 + c_2 + b_3(b-1) \left[-kc_1 - \bar{k}c_2 \right] \right] W_3 + \\
 & + \frac{1}{1-b^2} F_4[1-b-b_3(b-1)(k+\bar{k})] \\
 w_3' = & \pi \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) - \bar{k}(q_1 + c_2k) + b \left(-\frac{1}{2i\lambda_0} - kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right) \right] W_1 + \\
 & + \pi \left[b \left(\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1k) - \bar{k}(q_1 + c_2k) \right) - \frac{1}{2i\lambda_0} - kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k}) \right] W_2 \\
 & + \pi \left[b_3[-k(i\lambda_0 + c_1k) - \bar{k}(q_1 + c_2k) - kc_1\bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2\bar{k})] - kc_1 - \bar{k}c_2 \right] w_3 - F_4(k+\bar{k})
 \end{aligned}
 \tag{9}$$

$$\begin{aligned}
 |F4| \leq ML & \left[\frac{1}{-2i\lambda_0} [-\pi + \pi^2(-i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] \right. \\
 & + b[\pi - \pi^2(i\lambda_0 + q_1) + \bar{k}[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] W_1 \\
 & + \frac{1}{-2i\lambda_0} [b[-\pi + \pi^2(-i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] \\
 & + \pi - \pi^2(i\lambda_0 + q_1) + \bar{k}[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] W_2 \\
 & + \frac{1}{-2i\lambda_0} [b_3[-2i\lambda_0\pi^2 + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] \\
 & \left. + \bar{k}[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0)]] - 2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2i\lambda_0) W_3 \right]^{1+\beta}
 \end{aligned}$$

Lemma 5 [2] :

the transform

$$\left. \begin{aligned}
 w_1 &= re^{i\theta} \\
 w_2 &= re^{-i\theta} \\
 w_3 &= -r_3
 \end{aligned} \right\} \dots (10)$$

where $\theta \in [0, 2\pi]$

transform (9) into the following differential system :

$$\left. \begin{aligned}
 r' &= \mu_1 r + \mu_2 r_3 + \frac{e^{-i\theta}}{1-b^2} F_5[1-b-b_3(b-1)(k+\bar{k})] \\
 r' &= \mu_1^* r + \mu_2^* r_3 + \frac{e^{i\theta}}{1-b^2} F_5[1-b-b_3(b-1)(k+\bar{k})] \\
 r_3' &= \mu_1^{**} r + \mu_2^{**} r_3 - F_5[k+\bar{k}]
 \end{aligned} \right\} \dots (11)$$

where

$$\begin{aligned}
 \mu_1 &= \frac{\pi}{1-b^2} [i\lambda_0 + c_1 k - b(q_1 + c_2 k) + b_3(b-1) [\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) \\
 &- \bar{k}(q_1 + c_2 k)] + b[c_1 \bar{k} - b(-i\lambda_0 - q_1 + c_2 \bar{k}) + b_3(b-1) [-\frac{1}{2i\lambda_0} - kc_1 \bar{k} \\
 &- \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]] \\
 &+ \frac{\pi}{1-b^2} [b[i\lambda_0 + c_1 k - b(q_1 + c_2 k) + b_3(b-1) [\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) \\
 &- \bar{k}(q_1 + c_2 k)]] + c_1 \bar{k} - b(i\lambda_0 - q_1 + c_2 \bar{k}) + b_3(b-1) [-\frac{1}{2i\lambda_0} - kc_1 \bar{k} - \\
 &\bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]] e^{-2i\theta} \\
 \mu_2 &= -\frac{\pi e^{-i\theta}}{1-b^2} b_3 [i\lambda_0 + c_1 k - b(q_1 + c_2 k) + b_3(b-1) [-k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + \\
 &c_2 k)] + c_1 \bar{k} - b(-i\lambda_0 - q_1 + c_2 \bar{k}) + b_3(b-1) [-kc_1 \bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]] \\
 &- \frac{\pi e^{-i\theta}}{1-b^2} [c_1 - bc_2 + b_3(b-1) [-kc_1 - \bar{k}c_2]]. \\
 \mu_1^* &= \frac{\pi}{1-b^2} [-b(i\lambda_0 + c_1 k) + q_1 + c_2 k + b_3(b-1) [\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) \\
 &- \bar{k}(q_1 + c_2 k)] + b[-bc_1 \bar{k} - i\lambda_0 - q_1 + c_2 \bar{k} + b_3(b-1) [-\frac{1}{2i\lambda_0} - kc_1 \bar{k} \\
 &- \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]] e^{2i\theta} \\
 &+ \frac{\pi}{1-b^2} [b[-b(i\lambda_0 + c_1 k) + q_1 + c_2 k + b_3(b-1) [\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) \\
 &- \bar{k}(q_1 + c_2 k)]] - bc_1 \bar{k} - i\lambda_0 - q_1 + c_2 \bar{k} + b_3(b-1) [-\frac{1}{2i\lambda_0} - kc_1 \bar{k} - \\
 &\bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]]
 \end{aligned}$$

$$\begin{aligned}
 \mu_2^* &= -\frac{\pi e^{i\theta}}{1-b^2} b_3 [-b(i\lambda_0 + c_1 k) + q_1 + c_2 k + b_3(b-1)[-k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + \\
 &c_2 k)] - b c_1 \bar{k} - i\lambda_0 - q_1 + c_2 \bar{k} + b_3(b-1)[-k c_1 \bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})]] \\
 &- \frac{\pi e^{i\theta}}{1-b^2} [-b c_1 + c_2 + b_3(b-1)[-k c_1 - c_2 \bar{k}]] \\
 \mu_1^{**} &= -\pi \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + c_2 k) + b \left[-\frac{1}{2i\lambda_0} - k c_1 \bar{k} - \right. \right. \\
 &\left. \left. - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k}) \right] \right] e^{i\theta} \\
 &- \pi \left[b \left[\frac{1}{2i\lambda_0} - k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + c_2 k) \right] - \frac{1}{2i\lambda_0} - k c_1 \bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k}) \right] e^{-i\theta} \\
 \mu_2^{**} &= -\pi b_3 [-k(i\lambda_0 + c_1 k) - \bar{k}(q_1 + c_2 k) - k c_1 \bar{k} - \bar{k}(-i\lambda_0 - q_1 + c_2 \bar{k})] \\
 &- \pi [-k c_1 - \bar{k} c_2] \\
 |F5| &\leq ML \left[\frac{1}{-2i\lambda_0} [-\pi + \pi^2(-i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0)] \right. \\
 &+ b[\pi - \pi^2(i\lambda_0 + q_1) + \bar{k}[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0)]]] e^{i\theta} \\
 &+ [b[-\pi + \pi^2(i\lambda_0 + q_1) + k[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0)]] \\
 &+ \pi - \pi^2(i\lambda_0 + q_1) + \bar{k}[-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0)]]] e^{i\theta} r \\
 &- \frac{1}{-2i\lambda_0} [b_3 [-2i\lambda_0 \pi^2 + [k + \bar{k}](-2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0))] \\
 &\left. - 2i\lambda_0 + \pi^2(2(i\lambda_0)^3 + 2q_1(i\lambda_0)^2 + 2q_2 i\lambda_0) \right] r_3 \Big]^{1+\beta}
 \end{aligned}$$

4 – Fundamental results :

Theorem :

In the equation (1) if :

$$1- \quad p_s : \Delta = [a, \infty) \rightarrow \mathbb{C} \quad , \quad h : \Delta \times \mathbb{C}^n \rightarrow \mathbb{C} \quad ,$$

$$|h(t, y, y', y'')| \leq L^* [|y| + |y'| + |y''|]^{1+\beta}$$

$$L^* : \Delta \rightarrow [0, \infty) \quad , \quad \beta \geq 0$$

$$2- \quad \lim_{t \rightarrow \infty} \pi^{-2} \pi' = o(1) \quad , \quad \lim_{t \rightarrow \infty} W_s(t) = o(1)$$

and

a - if $\int_T^t \text{Re } \mu dt \rightarrow -\infty$ as $t \rightarrow \infty$

b - $e^{\int_T^t \text{Re } \mu dt} \int_T^t \mu_1 e^{-\int_T^t \text{Re } \mu dt} dt = o(1), t \rightarrow \infty$

then the zero solution of (1) is stable

c - if $\int_T^t \text{Re } \mu dt \rightarrow \infty$ as $t \rightarrow \infty$

then the zero solution of (1) is unstable

proof

on applying the transformation (2) ,(4) ,(8) and (10) into (1) we get the auxiliary system :

$$\begin{aligned}
 r' &= \mu_1 r + \mu_2 \xi_3 + \frac{e^{-i\theta}}{1-b^2} F_6 [1-b-b_3(b-1)(k+\bar{k})] \\
 r' &= \mu_1^* \xi_2 + \mu_2^* \xi_3 + \frac{e^{-i\theta}}{1-b^2} F_6 [1-b-b_3(b-1)(k+\bar{k})] \quad \dots(12) \\
 r_3' &= \mu_1^{**} \xi_1 + \mu_2^{**} r_3 - F_6 [k+\bar{k}]
 \end{aligned}$$

where $\xi = \xi(t)$ is an arbitrary variant function and it is continuous for all " $t \geq T$ " the auxiliary system (12) solved by the method Variation of parameters " [1]

$$|r| \leq e^{\int_T^t \text{Re } \mu_1 dt} [r(T) + \int_T^t (\mu_2 \xi_3 + \frac{e^{-i\theta}}{1-b^2} F_6 [1-b-b_3(b-1)(k+\bar{k})]) e^{-\int_T^t \text{Re } \mu_1(t) dt} dt] \quad \dots(13)$$

$$|r| \leq e^{\int_T^t \text{Re } \mu_1^* dt} [r(T) + \int_T^t (\mu_2^* \xi_3 + \frac{e^{i\theta}}{1-b^2} F_6 [1-b-b_3(b-1)(k+\bar{k})]) e^{-\int_T^t \text{Re } \mu_1^*(t) dt} dt] \quad \dots(14)$$

$$|r_3| \leq e^{\int_T^t \text{Re } \mu_2^{**} dt} [r(T) + \int_T^t (\mu_1^{**} \xi_1 - F_6 [(k+\bar{k})]) e^{-\int_T^t \text{Re } \mu_2^{**}(t) dt} dt] \quad \dots(15)$$

Now it is clear if

$$1- e^{\int_T^t \text{Re } \mu dt} = 0 \quad , \quad 2- e^{\int_T^t \text{Re } \mu^* dt} = 0 \quad , \quad 3- e^{\int_T^t \text{Re } \mu^{**} dt} = 0$$

then the zero solution of equation (1) is stable

To explain our fundamental results the following example is given:

Stability conditions of ...

$$y''' + \pi[(1-i)+(Int)^{-1}(2+3i)]y'' + \pi^2[4+(Int)^{-2}(1-4i)]y' + \pi^3[(4-4i)+t^{-1}(3-6i)]y = L^* [|y|+|y'|+|y''|]^{1+\beta} \dots\dots\dots (A), \quad \beta \in [0, \infty)$$

The characteristic equation to homogeneous part of equation (A)

Contains roots form : $\lambda_1 = 2i$, $\lambda_2 = -2i$, $\lambda_3 = -1 + i$

when $\lim_{t \rightarrow \infty} \pi^{-2} \pi' = o(1)$, $\lim_{t \rightarrow \infty} W_s(t) = o(1)$

$b = 1+i$, $b_3 = 1$, $k = 2+i$, $\bar{k} = 2 - i$

for example if $\pi = e^t$ or $\pi = -t^{-1/2}$ then $\lim_{t \rightarrow \infty} \pi^{-2} \pi' = o(1)$

on applying the transformation (2) ,(4) ,(8) and (10) into (A) we get the following table :

	$\pi = -t^{-1/2}$				$\pi = e^t$			
	$\theta=0$	$\theta=30$	$\theta=45$	$\theta=60$	$\theta=0$	$\theta=30$	$\theta=45$	$\theta=60$
$\int_T^t \text{Re } \mu_1 dt$	∞	$-\infty$	$-\infty$	$-\infty$	$-\infty$	∞	∞	∞
$\int_T^t \text{Re } \mu_1^* dt$	∞	∞	∞	∞	$-\infty$	$-\infty$	$-\infty$	$-\infty$
$\int_T^t \text{Re } \mu_2^{**} dt$	∞				$-\infty$			
	unstable				stable	unstable	unstable	unstable

REFERENCES

- [1] EL slogs ,L .E. (1977) Differential Equations and Calculus of Variation, India .
- [2] Malkin, I.G., (1966) .Theory of Stability of Motion , Moscow.Nauk publishing co. Moscow. Inc, USSR.
- [3] Miller, R. K.; Michel A. N., (1982) . Ordinary Differential Equations , London.Academic press,Inc.
- [4] Thanoon, T.Y, (1990). Center of Gravity of non-Autonomous Nonlinear Differential System in Some Critical Cases . Unpublished Ph.D. Thesis, Odessa, USSR .
- [5] Thanoon, T.Y, AL-Katib A.Z., (1999). “The Finding Conditions of Stability Trivial Solution for Certain Differential Equation in the Semi-linear Case , **J.Edu . Sci.**, Vol(37) , PP. 88-96 .
- [6] Thanoon, T.Y, Etewi J. R., (2001). On the Center of Gravity for Quasi – linear Differential Equation of Order n in the Critical Case , **J.Edu. Sci.**, Vol.(12), PP. 82 - 90 .